

TITAN X

LIFEP04 EMERGENCY CONVERSION KITS

Titan X emergency conversion kits utilise rechargeable LiFeP04 battery technology, to deliver a versatile solution. The compact, low profile design permits installation into shallow ceiling voids, whilst the 230V kit features a flexi-housing construction, to fit through 55mm ceiling cut outs. Each Kit is supplied with necessary connectors, indicators and bezel.



Features

- Versatile kit, fits into shallow ceiling voids
- 230V Kit features flexi-housing to fit small downlight ceiling cutouts
- Uses advanced technology LiFeP04 batteries
- Concise range - makes selection simple
- 230V version ideal for use with Red Arrow non-dimmable GU10 and T8 LED lamps
- Supplied with connectors (where appropriate), indicator, and bezel
- Self Test version ensures compliance with test regime regulations

Specification

Code	Description	Lumen Output	Emergency Lumen Output	Wattage	Efficacy
TITANX/4/KIT	Titan X Remote EM Conversion Kit 3Hr 4W DC10-80V			4W	

Product Information

Guarantee	5 Years	Material (Body/Housing)	Polycarbonate
Emergency Battery Guarantee	5 Years	Colour Finish	Black
On-Site Warranty	2 Years	Frequency	50/60Hz
IP Rating	IP20	Approval	UKCA CE

Emergency Battery Type	LiFePO4
Voltage	230V

Working Temperature	5°C to +35°C
EM Working Temperature	5°C to +35°C

EMERGENCY LIGHTING SPECIFICATION SHEET



TITAN X

LIFEP04 EMERGENCY CONVERSION KITS

Packaging Information

Dimensions (mm)	L: 245 x W: 67 x D: 32 mm
Product Net Weight (kg)	0.4 kg
Barcode	5055807625258

Units/Outer Carton	10
Outer Carton Barcode	15055807625255

